

NBC230, 430 Earth Leakage Circuit Breaker





NBC230 earth leakage with test button





circuit breaker

Application

NBC230 Breaker are suitable in AC 50Hz,250/440V circuit with overload and earth leakage protection. The rated current is adjustable from 10A up to 60A. User can select suitable current to better protection against overload and short circuit. The products comply with NFC61450.

Technical specification

Туре	NBC230 NBC430
Poles	2P 4P
Rated voltage (V)	250V/440V
Rated current (A)	10,15,20,25,30,45,50,60A Ajustable
Leakage motion current (mA)	300mA,500mA
Leakage dead current (mA)	150mA,250mA
Accord with standand	NFC 61450

KD-L & ELP-2530S SERIES Earth Leakage Circuit Beaker

Application

KD-L seriver earth leakage circuit breaker is used to AC 230V,50Hz rarrent to 30A, it used to boby electricity and overload protection it used to prevent from fire risk dllo to device destory.

It also used to protect wire overwad ctype 1and type3 must use with fuse cut-out.

This earth leakage ciecuit breaker is AC electroinc snap-action type. The product is complied with IE(755-1922 and GB6829-1955, GB16916, 1-1997 standard). The production win "CCC" CQC certificate.

Specification and technical data

1.13In

1.45In

2.55In

ELCB basic parameter

Rated Voltage (V)	Frequency (Hz)	pole	Rated Current(A)		Rated		Operating Time(s)	
			with load trip(A)	without load trip(A)	Sensitivity Current (mA)	Sensitivity Current (mA)	I∆n	0.25A
220-240	50-60Hz	2	10,16,20,30	20,30	30,15,10	15,7.5,6	0.1	0.04
Serial No. Examination Current			Incept State	e Examination Current				

cold

hot

cold



KD-L2123J(NEW)

KD-L2123J COVER

Dimensions(mm)

1

2

3







 $t \ge 1h$ non Actuation

t <1h Actuation

1<t<60s Actuation



KD-LS2123

